

Opus 3 Installation

230-240V / 50-60Hz
IP65



WARNING - THIS LUMINAIRE MUST BE EARTHED

This luminaire has been tested and is manufactured to comply with BS EN 60598 : specification for general requirements and tests. It should be installed by a suitably qualified person in accordance with IEE.

CAUTION: there is a potential risk of electric shock from the LED boards when the product is operational with the cover removed.

NOTE: INSTALLATION AND OPERATION OF THE LUMINAIRE BEYOND ITS SCOPE OF SUPPLY WILL INVALIDATE THE WARRANTY.

DIL-0269-0001

<p>1.</p> <p>Remove screws securing the frame and retain. Carefully remove the frame and glass and store safely.</p>	<p>2.</p> <p>Secure saddle bracket to a suitable surface making sure that all limitations have been observed. To adjust the angle of the saddle bracket, use an Allen key to loosen the Hex bolts in the sides. Retighten once at desired angle.</p>
<p>3.</p> <p>If mounting in an orientation shown, ensure fitting is angled by 10° to prevent water pooling on the front cover</p>	<p>4.</p> <p>Feed mains cable into body and wire into respective terminals. Ensure the cable clamp bar is used to secure the cable.</p>
<p>5.</p> <p>Ensure the cable gland is fully tightened. Under tightening may result in failure of IP65 rating.</p>	<p>6.</p> <p>Reverse step 1 to replace frame and glass. Do not exceed 1.5NM torque when securing front frame screws.</p>